


# Mercusys 8-Port Gigabit Desktop Switch

Model: MS108GS

Manufacturer: MERCUSYS

EAN: 6957939001339

Product Code: 200131

## R905

Certification: CE, RoHS | Operating temperature (T-T): 0 - 40 °C | Networking standards: IEEE 802.3i | Networking standards: IEEE 802.3x | Operating relative humidity (H-H): 10 - 90% | Storage relative humidity (H-H): 5 - 95% | DC input voltage: 5 V | Networking standards: IEEE 802.3 | Networking standards: IEEE 802.3ab | Auto MDI/MDI-X: Yes | Networking standards: IEEE 802.3u | Power supply included: Yes | Housing material: Metal | Input current: 0.6 A | Networking standards: IEEE 802.3p | MAC address table: 8000 entries | Auto-negotiation: Yes | Width: 158 mm | Switch type: Unmanaged | Power over Ethernet (PoE): No | Transmission distance (max): 0.1 km | AC input frequency: 50/60 Hz | Basic switching RJ-45 Ethernet ports type: Gigabit Ethernet (10/100/1000) | LED indicators: Yes | Storage temperature (T-T): -40 - 70 °C | Packet buffer memory: 0.5 MB | Basic switching RJ-45 Ethernet ports quantity: 8 | AC input voltage: 220 V | Heat dissipation: 14.348 BTU/h | Rack mounting: No | MAC address auto-aging supported: Yes | 10G support: No | Jumbo frames support: Yes | Manual: Yes | Height: 25.2 mm | Wall mountable: Yes | Cables included: AC | Product colour: Black | MAC address auto-learning supported: Yes | Stackable: No | Flow control support: Yes | Fanless: Yes | Depth: 99.1 mm | Quick start guide: Yes | Power consumption (max): 4.22 W | Full duplex: Yes | Power connector: DC-in jack | Power source: DC | Switching capacity: 16 Gbit/s | Jumbo

The product information provided is for reference purposes only. Technical specifications, photos, descriptions and prices may change without prior notice. The manufacturer and seller are not responsible for possible data discrepancies or typographical errors. We recommend checking the current information before purchasing.
shop.cssi.co.za | sales@cssi.co.za | +27 (11)541-9950

frames: 15000 | Store-and-forward: Yes | Half duplex: Yes | Warnings: Ensure the unit is adequately ventilated during operation. | Warnings: The product is not suitable for disposal in the regular waste bin. Take your used electronic equipment to a recycling centre in accordance with local regulations. | Warnings: Do not open the case or try to repair it yourself.

The product information provided is for reference purposes only. Technical specifications, photos, descriptions and prices may change without prior notice. The manufacturer and seller are not responsible for possible data discrepancies or typographical errors. We recommend checking the current information before purchasing.
shop.cssi.co.za | sales@cssi.co.za | +27 (11)541-9950